

FUJITSU Enterprise Postgres 14 on IBM LinuxONE

Release Notes

Linux



Preface

Purpose of this document

This document provides release information for FUJITSU Enterprise Postgres.

Structure of this document

This document is structured as follows:

[Chapter 1 New Features and Improvements](#)

Explains the new features and improvements in this version.

[Chapter 2 Compatibility Information](#)

Provides information regarding compatibility.

Export restrictions

Exportation/release of this document may require necessary procedures in accordance with the regulations of your resident country and/or US export control laws.

Issue date and version

Edition 1.0: February 2022

Copyright

Copyright 2019-2022 FUJITSU LIMITED

Contents

Chapter 1 New Features and Improvements.....	1
1.1 Features Added in 14.....	1
1.1.1 Operation.....	1
1.1.1.1 Connection Manager.....	1
1.1.2 OSS.....	1
1.1.2.1 PostgreSQL Rebase.....	1
1.1.2.2 Update of OSS Provided.....	2
1.1.3 Platform enhancement.....	2
1.1.3.1 Additional Operating System Support for Server Feature.....	2
1.1.3.2 Additional Operating System Support for Client Feature.....	2
1.1.3.3 Additional Operating System Support for Server Assistant Feature.....	2
Chapter 2 Compatibility Information.....	3
2.1 Installation/Setup Incompatibility.....	3
2.1.1 Removing Operating System Support.....	3
2.1.2 Changing kernel parameter settings when an instance is created with WebAdmin.....	3
2.1.3 Removing Operating System Support.....	4
2.1.4 Changing the Way OSS is Set Up.....	5
2.1.5 Modifying Pgpool-II Installation Handling.....	5
2.1.6 Changing Core and Log File Paths when Instance is Created with WebAdmin.....	5
2.1.7 Renaming WebAdmin Services.....	6
2.2 Application Migration Incompatibility.....	6
2.2.1 Changing the display result when data masking is applied to NaN, infinity, -infinity.....	6
2.2.2 Changing the Valid Range of Identifiers Defined by the DECLARE STATEMENT statement.....	7
2.2.3 Changing Precompile Results.....	7
2.2.4 Changing the Trigger Replacement Process.....	7
2.2.5 Removing Java Support.....	8
2.2.6 Changed to Error when Running an Operator or Function that Returns non Data Types for Masking Type.....	8
2.3 Operation Migration Incompatibility.....	9
2.3.1 Changing the Output of the Status Mode of the cm_ctl Command.....	9
2.3.2 Rename column "master_pid" in pgx_loader_state to "leader_pid".....	10
2.3.3 Adding a Message to Output when the Database Server watchdog detects that the Connection Manager is down.....	10
2.3.4 Change the Error Information when the Connection Manager re-executes SQL on the Failed Connection.....	11
2.3.5 Changing the Value of the Category Column in the pg_settings view.....	12
2.3.6 Changing pgx_stat_lwlock of the Statistics View.....	12
2.3.7 Changing the Behavior of pgx_rcvall.....	13
2.3.8 Mirroring Controller no Longer Retries to Monitor Database Processes when they are Detected as Down.....	13
2.3.9 Changing the Name and Parameter Name of the Mirroring Controller Post-Promote Command.....	14
2.3.10 Changing Mirroring Controller User Command Input Values.....	14
2.4 JDBC Drive Incompatibility.....	14
2.4.1 Changing the targetServerType Value.....	15
2.5 ODBC Drive Incompatibility.....	15
2.5.1 Cannot specify prefer-read for target_session_attrs.....	15
2.6 C Library (libpq) Migration Incompatibility.....	15
2.6.1 Changing when "prefer-read" is Specified for the target_session_attrs Parameter.....	16
2.7 oracle_fdw Incompatibility.....	16
2.7.1 Changing the Oracle Client Version.....	16
2.8 pgaudit Incompatibility.....	16
2.8.1 Changing to Output Extra NEW and OLD Values in the Audit Log when the Trigger Function Executes.....	17
2.9 WebAdmin Incompatibility.....	17
2.9.1 Cannot specify prefer-read for target_session_attrs.....	17
2.10 Connection Manager Incompatibility.....	18
2.10.1 Behavior change when "read-write" is specified for the target_session_attrs parameter.....	18
Index.....	19

Chapter 1 New Features and Improvements

This chapter explains FUJITSU Enterprise Postgres new features and improvements added in this version.

Table 1.1 New features and improvements

Version and level	Classification	Feature
14	Operation	Connection Manager
	OSS	PostgreSQL Rebase
		Update of OSS Provided
	Platform enhancement	Additional Operating System Support for Server Feature
		Additional Operating System Support for Client Feature
		Additional Operating System Support for Server Assistant Feature

1.1 Features Added in 14

This section explains new features and improvements in FUJITSU Enterprise Postgres 14.

1.1.1 Operation

This section explains the new features and improvements related to operation:

- Connection Manager

1.1.1.1 Connection Manager

Connection Manager is now available to the following client drivers:

- ODBC driver
- JDBC driver



Refer to Connection Manager User's Guide for details.

1.1.2 OSS

This section explains the new feature related to OSS:

- PostgreSQL rebase
- Update of OSS provided

1.1.2.1 PostgreSQL Rebase

The PostgreSQL version that FUJITSU Enterprise Postgres is based on is 14.0.



Refer to "PostgreSQL Version Used for FUJITSU Enterprise Postgres" in the Installation and Setup Guide for Server for details.

1.1.2.2 Update of OSS Provided

The OSS provided by FUJITSU Enterprise Postgres have been updated.



.....
Refer to "OSS Supported by FUJITSU Enterprise Postgres" in the General Description for details.
.....

1.1.3 Platform enhancement

This section explains the new features related to platform enhancement:

- Additional operating system support for server
- Additional operating system support for client
- Additional operating system support for server assistant

1.1.3.1 Additional Operating System Support for Server Feature

The following additional operating system is supported:

- SLES 15 SP3



.....
Refer to "Required Operating System" in the Installation and Setup Guide for Server for details.
.....

1.1.3.2 Additional Operating System Support for Client Feature

The following additional operating system is supported:

- SLES 15 SP3



.....
Refer to "Required Operating System" in the Installation and Setup Guide for Server for details.
.....

1.1.3.3 Additional Operating System Support for Server Assistant Feature

The following additional operating system is supported:

- SLES 15 SP3



.....
Refer to "Required Operating System" in the Installation and Setup Guide for Server Assistant for details.
.....

Chapter 2 Compatibility Information

This chapter explains incompatible items and actions required when migrating from an earlier version to FUJITSU Enterprise Postgres 14. Check compatibility before migrating and take the appropriate action.

2.1 Installation/Setup Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Removing Operating System Support	Y	Y	Y	N
Changing kernel parameter settings when an instance is created with WebAdmin	Y	Y	Y	N
Removing Operating System Support	Y	Y	N	N
Changing the way OSS is set up	Y	N	N	N
Modifying Pgpool-II Installation Handling	Y	N	N	N
Changing Core and Log File Paths when Instance is Created with WebAdmin	Y	N	N	N
Renaming WebAdmin Services	Y	N	N	N

Y: Incompatibility exists

N: Incompatibility does not exist

2.1.1 Removing Operating System Support

Incompatibility

In FUJITSU Enterprise Postgres 13 or later, the following operating systems have been removed.

- RHEL7.7 and later minor version
- RHEL8.1

Action method

None.

2.1.2 Changing kernel parameter settings when an instance is created with WebAdmin

Incompatibility

For FUJITSU Enterprise Postgres 13 and later, changes kernel parameter settings for WebAdmin instance creation.

FUJITSU Enterprise Postgres 12 SP1 or earlier

Kernel Parameters	Value	Calculated Value
SHMMAX	If <i>currentValue</i> < <i>calculatedValue</i> , configure the calculated value	$((1800 + 270 * \text{max_locks_per_transaction}) * \text{max_connections} + (1800 + 270 * \text{max_locks_per_transaction}) * \text{autovacuum_max_workers} + (770 + 270 * \text{max_locks_per_transaction}) * \text{max_prepared_transactions} +$

Kernel Parameters	Value	Calculated Value
		$(\text{shared_buffer}) + (16 * 1024 * 1024) + (770 * 1024) * 1.05$
SHMALL	Specify <i>currentValue</i> + <i>calculatedValue</i>	$(\text{SHMMAX} / \text{PAGESIZE}) + 1$ $\text{PAGESIZE} = 4\text{K}$
SEMMNI	Specify <i>currentValue</i> + <i>calculatedValue</i>	$\text{ceil}((\text{max_connections} + \text{autovacuum_max_workers} + 4) / 16)$
SEMMNS	Specify <i>currentValue</i> + <i>calculatedValue</i>	$\text{ceil}((\text{max_connections} + \text{autovacuum_max_workers} + 4) / 16) * 17$

FUJITSU Enterprise Postgres 13 or later

Kernel Parameters	Value	Calculated Value
SHMMAX	Do not change value	-
SHMALL	Do not change value	-
SEMMNI	Specify <i>currentValue</i> + <i>calculatedValue</i>	<p>- For instances of FUJITSU Enterprise Postgres 11:</p> $\text{ceil}((\text{max_connections} + \text{autovacuum_max_workers} + \text{max_worker_processes} + 5) / 16)$ <p>- For Fujitsu Enterprise Postgres 12 and later instances:</p> $\text{ceil}((\text{max_connections} + \text{autovacuum_max_workers} + \text{max_wal_senders} + \text{max_worker_processes} + 5) / 16)$
SEMMNS	Specify <i>currentValue</i> + <i>calculatedValue</i>	<p>- For instances of FUJITSU Enterprise Postgres 11:</p> $\text{ceil}((\text{max_connections} + \text{autovacuum_max_workers} + \text{max_worker_processes} + 5) / 16) * 17$ <p>- For Fujitsu Enterprise Postgres 12 and later instances:</p> $\text{ceil}((\text{max_connections} + \text{autovacuum_max_workers} + \text{max_wal_senders} + \text{max_worker_processes} + 5) / 16) * 17$

Action method

None.

2.1.3 Removing Operating System Support

Incompatibility

In FUJITSU Enterprise Postgres 12 SP1 or later, the following operating systems have been removed.

- SLES 12 SP4

Action method

None.

2.1.4 Changing the Way OSS is Set Up

Incompatibility

FUJITSU Enterprise Postgres 12 or later do not place OSS extension modules in the executable directory. The OSS extension modules must be placed in the executable directory when you set up OSS.

Refer to "Setting Up and Removing OSS" in the Installation and Setup Guide for Server for details.

Action method

None.

2.1.5 Modifying Pgpool-II Installation Handling

Incompatibility

For FUJITSU Enterprise Postgres 12 or later, Pgpool-II is not automatically installed when you install the server. Therefore, if you want to take advantage of Pgpool-II, install it separately from the server installation.

The extension modules required for the database server are shipped with the server program. You should set up Pgpool-II on the database server side, even if Pgpool-II is to be used on a different server than the database server.

Refer to "Setting Up and Removing OSS" in the Installation and Setup Guide for Server for details.

Action method

None.

2.1.6 Changing Core and Log File Paths when Instance is Created with WebAdmin

Incompatibility

In FUJITSU Enterprise Postgres 12 or later, change the core and log file paths when creating an instance in WebAdmin.

FUJITSU Enterprise Postgres 11

Log File Path: `/var/tmp/fsep_version/instanceAdminUser_instanceNamePortNumber/log`

Core File Path: `/var/tmp/fsep_version/instanceAdminUser_instanceNamePortNumber/core`

version: product version_edition_architecture

[Example]

Log File Path: `/var/tmp/fsep_110_AE_64/naomi_myinst27599/log`

Core File Path: `/var/tmp/fsep_110_AE_64/naomi_myinst27599/core`

FUJITSU Enterprise Postgres 12

Log File Path: `/var/tmp/fsep_version/instanceAdminUser_instanceNamePortNumber/log`

Core File Path: `/var/tmp/fsep_version/instanceAdminUser_instanceNamePortNumber/core`

version: product version_WA_architecture

[Example]

Log File Path: `/var/tmp/fsep_120_WA_64/naomi_myinst27599/core`

Core File Path: `/var/tmp/fsep_120_WA_64/naomi_myinst27599/log`

Action method

None.

2.1.7 Renaming WebAdmin Services

Incompatibility

In FUJITSU Enterprise Postgres 12 or later, change the service name registered when you set up WebAdmin.

FUJITSU Enterprise Postgres 11

fsep_xSPz_edition_64_WebAdmin_Port1

fsep_xSPz_edition_64_WebAdmin_Port2

FUJITSU Enterprise Postgres 12 or later

fsep_xSPz_WA_64_WebAdmin_Port1

fsep_xSPz_WA_64_WebAdmin_Port2

Action method

None.

2.2 Application Migration Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Changing the display result when data masking is applied to NaN, infinity, -infinity	Y	Y	Y	Y
Changing the Valid Range of Identifiers Defined by the DECLARE STATEMENT statement	Y	Y	Y	Y
Changing Precompile Results	Y	Y	Y	Y
Changing the Trigger Replacement Process	Y	Y	Y	Y
Removing Java Support	Y	Y	Y	N
Changed to Error when Running an Operator or Function that Returns non Data Types for Masking Type	Y	N	N	N

Y: Incompatibility exists

N: Incompatibility does not exist

2.2.1 Changing the display result when data masking is applied to NaN, infinity, -infinity

Incompatibility

In FUJITSU Enterprise Postgres 14, the display result when data masking is applied to NaN, infinity, and -infinity will be changed.

FUJITSU Enterprise Postgres 13 or earlier

If the float type NaN, infinity, and -infinity are partially masking with (9,1,2), the following will be displayed.

NaN : 99

Infinity : 99

-Infinity : 99

FUJITSU Enterprise Postgres 14 or later

If the float type NaN, infinity, and -infinity are partially masking with (9,1,2), the following will be displayed.

```
NaN : NaN
Infinity : Infinity
-Infinity : -Infinity
```

Action method

If the application is analyzing the SQL masking output result, please consider the non-numeric output result and correct it.

2.2.2 Changing the Valid Range of Identifiers Defined by the DECLARE STATEMENT statement

Incompatibility

In FUJITSU Enterprise Postgres 14 will change the valid range of identifiers defined by a DECLARE STATEMENT statement in ecpg/ecobpg.

FUJITSU Enterprise Postgres 13 or earlier

The valid range is now per process.

FUJITSU Enterprise Postgres 14 or later

The valid range is now per file.

Action method

None.

2.2.3 Changing Precompile Results

Incompatibility

In FUJITSU Enterprise Postgres 14 removed the ECPGdeclare/ECPGopen function. Therefore, results precompiled from earlier versions of FUJITSU Enterprise Postgres will not be available in FUJITSU Enterprise Postgres 14.

Action method

Rebuild the application.

2.2.4 Changing the Trigger Replacement Process

Incompatibility

In FUJITSU Enterprise Postgres 14 will change restricted triggers to not be supported by replace operations (OR REPLACE).

FUJITSU Enterprise Postgres 13 or earlier

You can replace a constraint trigger.

[Example]

```
=# CREATE OR REPLACE CONSTRAINT TRIGGER my_constraint_trigger AFTER DELETE ON my_table
-# FOR EACH ROW
-# EXECUTE PROCEDURE funcA();
CREATE TRIGGER
```

FUJITSU Enterprise Postgres 14 or later

It does not support replacing a constraint trigger.

[Example]

```
=# CREATE OR REPLACE CONSTRAINT TRIGGER my_constraint_trigger AFTER DELETE ON my_table
-# FOR EACH ROW
-# EXECUTE PROCEDURE funcA();
ERROR: CREATE OR REPLACE CONSTRAINT TRIGGER is not supported
```

Action method

None.

2.2.5 Removing Java Support

Incompatibility

In FUJITSU Enterprise Postgres 13 or later, the following Java have been removed.

- Java SE 6

Also, the JDBC driver file 'postgresql-jdbc4.jar' for JDK 6 or JRE 6 isn't installed.

Action method

None.

2.2.6 Changed to Error when Running an Operator or Function that Returns non Data Types for Masking Type

Incompatibility

In FUJITSU Enterprise Postgres 12, changed to error when running an operator or function that returns non Data Types for Masking type.

FUJITSU Enterprise Postgres 11

In the following cases, the operator or function in 3) may be executed without masking.

This is an incorrect result because the data containing the masking column is performed without masking.

- 1) Create a Masking policy. and
- 2) Execute a SELECT statement. and
- 3) Execute an operator or function in the SELECT statement of 2). and
- 4) The operator or function argument of 3) includes a subquery. and
- 5) The operator or function argument of 3) contains the column to be protected created in 1). and
- 6) The operator or function of 3) returns a type not listed in "Data Types for Masking" in "Operation Guide".

FUJITSU Enterprise Postgres 12 or later

Operator or function results of 3) in the following error.

```
ERROR: The output data type is incompatible with the confidential policy.
HINT: Data type of the result value(s) produced by expression/function using confidential columns
is not supported by Data masking module. Consider removing confidential columns from such
expressions/functions.
```

This is correct because the operator or function returns a data type not listed in "Data Types for Masking" in "Operation Guide".

Action method

Do one of the following to ensure that the results are identical to those of FUJITSU Enterprise Postgres 11:

- 1) Modify the Masking policy to prevent masking from being performed for the user executing the SQL.
- 2) Modify SQL to not use operators or functions that return types not listed in "Data Types for Masking" in "Operation Guide".

2.3 Operation Migration Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Changing the Output of the Status Mode of the cm_ctl Command	Y	Y	Y	Y
Rename column "master_pid" in pgx_loader_state to "leader_pid"	Y	Y	Y	Y
Adding a Message to Output when the Database Server watchdog detects that the Connection Manager is down	N	Y	Y	Y
Change the Error Information when the Connection Manager re-executes SQL on the Failed Connection	N	Y	Y	Y
Changing the Value of the Category Column in the pg_settings view	Y	Y	Y	N
Changing pgx_stat_lwlock of the Statistics View	Y	Y	Y	N
Changing the Behavior of pgx_rcvall	Y	Y	Y	N
Mirroring Controller no longer retries to monitor database processes when they are detected as down	Y	N	N	N
Changing the Name and Parameter Name of the Mirroring Controller Post-Promote Command	Y	N	N	N
Changing Mirroring Controller User Command Input Values	Y	N	N	N

Y: Incompatibility exists

N: Incompatibility does not exist

2.3.1 Changing the Output of the Status Mode of the cm_ctl Command

Incompatibility

Changes the display of the output of the status mode of the cm_ctl command.

(If it has been modified by the P number PH21029, and you have applied an urgent fix that includes it, FUJITSU Enterprise Postgres 14 will work.)

When the cm_ctl command was executed in status mode, there was omission of the output of the header "pid" displayed in "application_information" which outputs the information of the application.

Correct the following in PH21029.

- Add ':' to 'application_information' to output application information
Output "application_information:"
- Add the header "pid" output to "application_information"
Outputs "pid" whose header information is missing.

- Changes the number of digits in the numeric portion of `connected_time`
Change the display start position of the date and time connected to the `connmgr` process to correct the gap between the start position of the header and the numeric part. (5 digits backward)

This fix causes the following incompatibilities when running the `cm_ctl` command in status mode:

- Add ":" to the display of "application_information"
- Display the header "pid" in "application_information"
- Change the output start position of the "connected_time" header of "application_information"
- Change the start of the date and time output of "connected_time" in "application_information" to 5 digits later.

FUJITSU Enterprise Postgres 13 or earlier

```
application_information
addr      port  connected_time
10.xxx.x.xx 99999 21655 2021-10-20 09:18:51
```

FUJITSU Enterprise Postgres 14

```
application_information:
addr      port  pid      connected_time
10.xxx.x.xx 99999 21655    2021-10-20 09:18:51
```

When analyzing the output of the `cm_ctl` command in status mode in a batch or shell script, it may not work correctly if the header is referenced and the third is "connected_time".

For example, when identifying a row of data (numeric part), a string up to the header "addr", "port", and "connected_time" one row before is searched for and identified.

Action method

If you are using a batch or shell script to parse the output of the `cm_ctl` command in status mode, modify it to take into account the number of digits in the header and numeric part of the output.

2.3.2 Rename column "master_pid" in `pgx_loader_state` to "leader_pid"

Incompatibility

In FUJITSU Enterprise Postgres 14 renames column "master_pid" to "leader_pid" in the `pgx_load_state` table.

Action method

None.

2.3.3 Adding a Message to Output when the Database Server watchdog detects that the Connection Manager is down

Incompatibility

In FUJITSU Enterprise Postgres 13 SP1, when using the Connection Manager, if the database server watchdog detects that the Connection Manager is down, it will output a message to the database server.

Incompatibilities may occur if:

- 1) The application server is using the Connection Manager. and
- 2) The database server is running the watchdog process. and
- 3) 1) Application server or Connection Manager goes down.

FUJITSU Enterprise Postgres 13 or earlier

If the database server watchdog detects that the Connection Manager is down, the following message is not output.

```
WARNING:  watchdog: error in heartbeat connection (20331): host=xxx.xxx.xxx.xxx port=xxxxx  
pid=xxxxxx
```

FUJITSU Enterprise Postgres 14

If the database server watchdog detects that the Connection Manager is down, the following message may be output.

```
WARNING:  watchdog: error in heartbeat connection (20331): host=xxx.xxx.xxx.xxx port=xxxxx  
pid=xxxxxx
```

Action method

If you are monitoring the database log for watchdog messages, change the monitoring setting to one that takes into account the possible output of these messages.

2.3.4 Change the Error Information when the Connection Manager re-executes SQL on the Failed Connection

Incompatibility

In FUJITSU Enterprise Postgres 13 SP1 allows an application using the Connection Manager to change the error information when attempting to execute SQL again on a connection that the Connection Manager has determined to be in error due to a database error.

The changed error information is included in the error presented in "Errors when an Application Connection Switch Occurs and Corresponding Actions" for each client driver in "Application Development Guide".

Incompatibilities may occur if the following conditions are met:

- 1) The application uses one of the following drivers. and
-libpq (C Library)
-ECPG (Embedded SQL in C)
- 2) You are using the Connection Manager. and
- 3) The database server to which the application in 1) was connected goes down. and
- 4) The Connection Manager notifies the application in 1) of an error when the database is down in 3). and
- 5) The application in 1) does not disconnect from the database server that is down, but executes SQL using the connection.

FUJITSU Enterprise Postgres 13 or earlier

The error information returned depends on the actual database server error condition.

FUJITSU Enterprise Postgres 14

The following error information is returned:

- For libpq (C Library): CONNECTION_BAD (PQstatus () return value)
- For ECPG (Embedded SQL in C): 57P02 (SQLSTATE return value)

Action method

Consider that the above error may be returned during the SQL error determination process.

Also, if you encounter an error about switching application destinations as described in "Errors when an Application Connection Switch Occurs and Corresponding Actions" for each client driver in "Application Development Guide", you should explicitly disconnect and reconnect or rerun the application.

2.3.5 Changing the Value of the Category Column in the pg_settings view

Incompatibility

For FUJITSU Enterprise Postgres 13, change the value of the category column in the pg_settings view.

FUJITSU Enterprise Postgres 12 SP1 or earlier

Original value	wrong value
Preset Options	Fujitsu Enterprise Postgres Parameters
Customized Options	Preset Options
Developer Options	Customized Options

This is an incorrect result because it is different from the original value.

FUJITSU Enterprise Postgres 13 or later

The correct value is the category column in the pg_settings view.

Action method

Replaces the category column in the pg_settings view with the values before migration, so that the results are the same as before migration.

2.3.6 Changing pgx_stat_lwlock of the Statistics View

Incompatibility

In FUJITSU Enterprise Postgres 13, change the wait event name displayed in the lwlock_name column of the statistics view pgx_stat_lwlock.

Wait Event Name

FUJITSU Enterprise Postgres 12 SP1 or earlier	FUJITSU Enterprise Postgres 13
clog (*1)	XactBuffer
commit_timestamp (*1)	CommitTSBuffer
subtrans (*1)	SubtransBuffer
multixact_offset (*1)	MultiXactOffsetBuffer
multixact_member (*1)	MultiXactMemberBuffer
async (*1)	NotifyBuffer
oldserxid (*1)	SerialBuffer
wal_insert (*1)	WALInsert
buffer_content (*1)	BufferContent
buffer_io (*1)	BufferIO
replication_origin (*1)	ReplicationOriginState
replication_slot_io (*1)	ReplicationSlotIO
proc (*1)	LockFastPath
buffer_mapping (*1)	BufferMapping
lock_manager (*1)	LockManager
predicate_lock_manager (*1)	PredicateLockManager
parallel_hash_join (*1)	ParallelHashJoin
parallel_query_dsa (*1)	ParallelQueryDSA

FUJITSU Enterprise Postgres 12 SP1 or earlier	FUJITSU Enterprise Postgres 13
session_dsa (*1)	PerSessionDSA
session_record_table (*1)	PerSessionRecordType
session_typmod_table (*1)	PerSessionRecordTypmod
shared_tupstore (*1)	SharedTupleStore
tbm (*1)	SharedTidBitmap
parallel_append (*1)	ParallelAppend
serializable_xact (*2)	PerXactPredicateList
shared_mcxt (*2)	SharedMcxt
meta_cache_map (*2)	MetaCacheMap
global_metacache (*2)	GlobalCatcache
cached_buf_tranche_id (*2)	CachedBufTranche

*1) Events added in FUJITSU Enterprise Postgres 11.

*2) Events added in FUJITSU Enterprise Postgres 12.

Action method

None.

2.3.7 Changing the Behavior of pgx_rcvall

Incompatibility

In FUJITSU Enterprise Postgres 13, change the pgx_rcvall command to fail if the -e option of the pgx_rcvall command specifies a future time or if the -n option specifies a list appointment that does not exist.

FUJITSU Enterprise Postgres 12 SP1 or earlier

All archived WALs are applied for recovery if the -e option of the pgx_rcvall command specifies a time in the future, or if the -n option specifies a list appointment that does not exist.

FUJITSU Enterprise Postgres 13 or later

The pgx_rcvall command fails if the -e option of the pgx_rcvall command specifies a time in the future, or if the -n option specifies a list appointment that does not exist.

Action method

Specify recovery objectives correctly, if necessary.

2.3.8 Mirroring Controller no Longer Retries to Monitor Database Processes when they are Detected as Down

Incompatibility

For the FUJITSU Enterprise Postgres Mirroring Controller, change the heartbeat monitoring of the database process so that it does not retry monitoring when it detects down.

Action method

None.

2.3.9 Changing the Name and Parameter Name of the Mirroring Controller Post-Promote Command

Incompatibility

In the FUJITSU Enterprise Postgres 12 Mirroring Controller, change the name of the post-promote command, which is the state transition command, and the parameter name in the server configuration file that specifies the post-promote command.

FUJITSU Enterprise Postgres 11

- Command Name
post-promote command
- The parameter name in the server configuration file that specifies the post-promote command
post_promote_command

FUJITSU Enterprise Postgres 12 or later

- Command Name
post-switch command
- The parameter name in the server configuration file that specifies the post-promote command
post_switch_command

Action method

The post_promote_command parameter in the server configuration file continues to be available in FUJITSU Enterprise Postgres 12 or later. If specified in the server configuration file, it acts as a post-switch command. You cannot specify the post_promote_command and post_switch_command parameters at the same time.

2.3.10 Changing Mirroring Controller User Command Input Values

Incompatibility

Arguments (Fixed value: primarycenter) have been added to the following user commands:

- Fencing command of the database server
- Arbitration command
- Post-switch command
- Pre-detach command
- Post-attach command

Action method

If you are checking the number of arguments in a user command, increase the number of arguments by one.

2.4 JDBC Drive Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Changing the targetServerType Value	Y	Y	Y	N

Y: Incompatibility exists

N: Incompatibility does not exist

2.4.1 Changing the targetServerType Value

Incompatibility

In FUJITSU Enterprise Postgres 13, the value of targetServerType specified in the connection string was changed. Therefore, the previously used values are no longer available.

Action method

If you specified a value for targetServerType, change the value as follows:

Table 2.1 Specified values for the target server

Server Selection Order	FUJITSU Enterprise Postgres 12 SP1 or earlier	FUJITSU Enterprise Postgres 13
Primary Server	master	primary
Standby Server	slave	secondary
Prefer Standby Server	preferSlave	preferSecondary
Any	any	any

2.5 ODBC Drive Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Cannot specify prefer-read for target_session_attrs	Y	Y	Y	Y

Y: Incompatibility exists

N: Incompatibility does not exist

2.5.1 Cannot specify prefer-read for target_session_attrs

Incompatibility

FUJITSU Enterprise Postgres 14 users will not see the "prefer-read" radio button in the "Target_Session_Attrs" item of the data source option selection screen.

Action method

Select prefer-standby.

2.6 C Library (libpq) Migration Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Changing when "prefer-read" is Specified for the target_session_attrs Parameter	Y	Y	Y	Y

Y: Incompatibility exists

N: Incompatibility does not exist

2.6.1 Changing when "prefer-read" is Specified for the target_session_attrs Parameter

Incompatibility

In FUJITSU Enterprise Postgres 14 changes the attach server priority if any of the following servers are specified simultaneously with "prefer-read" as the target_session_attrs parameter:

- Primary server (default_transaction_read_only = ON)
- Standby server

FUJITSU Enterprise Postgres 13 or earlier

The primary server (default_transaction_read_only = ON) and standby servers have the same priority.

FUJITSU Enterprise Postgres 14 or later

Standby servers connect in preference to primary servers (default_transaction_read_only = ON).

Action method

None.

2.7 oracle_fdw Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Changing the Oracle Client Version	Y	N	N	N

Y: Incompatibility exists

N: Incompatibility does not exist

2.7.1 Changing the Oracle Client Version

Incompatibility

FUJITSU Enterprise Postgres 12 change the version of the Oracle client used to build oracle_fdw to 11.2.

Action method

Use Oracle client version 11.2 or later.

Also, if a file named libclntsh.so.11.1 does not exist in OCI library, create a symbolic link named libclntsh.so.11.1.

2.8 pgaudit Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Changing to Output Extra NEW and OLD Values in the Audit Log when the Trigger Function Executes	Y	Y	Y	N

Y: Incompatibility exists

N: Incompatibility does not exist

2.8.1 Changing to Output Extra NEW and OLD Values in the Audit Log when the Trigger Function Executes

Incompatibility

In FUJITSU Enterprise Postgres 13, the trigger function additionally outputs NEW and OLD values to the audit log when the `pgaudit.log_parameter` is set to on.

FUJITSU Enterprise Postgres 12 SP1 or earlier

The following (18) does not output the values of NEW, OLD.

[Example]

```
AUDIT: SESSION,WRITE,2020-09-03 07:07:39 UTC,
      (1)      (2)      (3)
[local],9775,psql,k5user,postgres,3/536, 1, 2, INSERT, ,
(4)      (5) (6) (7)      (8)      (9)  (10)(11)(12)(13)
TABLE,public.trig_audit, ,
(14) (15)      (16)
"INSERT INTO trig_audit SELECT 'U', now(), user, OLD.*, NEW.*",
(17)
trig_audit AFTER ROW UPDATE 92027 trig_test trig_test public 0 f aaaa
(18)
```

FUJITSU Enterprise Postgres 13 or later

NEW, OLD values are output.

[Example]

```
AUDIT: SESSION,WRITE,2020-09-03 07:07:39 UTC,
[local],9775,psql,k5user,postgres,3/536,1,2,INSERT,,TABLE,public.
trig_audit,,
"INSERT INTO trig_audit SELECT 'U', now(), user, OLD.*, NEW.*",
(bbb) (aaa) trig_audit AFTER ROW UPDATE 92027 trig_test trig_test
public 0 f aaaa
```

Action method

If you are using an application that works by monitoring the string that the trigger function output to the audit log, modify the application to work with the NEW and OLD values.

2.9 WebAdmin Incompatibility

Item	Pre-migration version			
	11	12	12 SP1	13
Cannot specify prefer-read for target_session_attrs	Y	Y	Y	Y

Y: Incompatibility exists

N: Incompatibility does not exist

2.9.1 Cannot specify prefer-read for target_session_attrs

Incompatibility

FUJITSU Enterprise Postgres 14 will no longer allow prefer-read to `target_session_attrs` as a connection method to an upstream server that is specified when creating an instance of a standby server.

Action method

Specify prefer-standby.

2.10 Connection Manager Incompatibility

Item	Pre-migration version		
	12	12 SP1	13
Behavior change when "read-write" is specified for the <code>target_session_attrs</code> parameter	Y	Y	Y

Y: Incompatibility exists

N: Incompatibility does not exist

2.10.1 Behavior change when "read-write" is specified for the `target_session_attrs` parameter

Incompatibility

FUJITSU Enterprise Postgres 13 or earlier

May be connected to primary server (`default_transaction_read_only = ON`).

FUJITSU Enterprise Postgres 14 or later

It is not connected to the primary server (`default_transaction_read_only = ON`).

Action method

For FUJITSU Enterprise Postgres 13 and earlier, specify "primary" for the `target_session_attrs` parameter.

Index

[C]

Compatibility Information.....3

[F]

Features Added in 14.....1